



The 41.0 is Coda's flagship Class A stereo amplifier. 56 high-bandwidth fifteen-ampere output devices provide high-current output into virtually any load with a frequency response reaching from 100kHz down to DC. The optional remote control allows input selection and bias control, and internal controls allow the 41.0 to be bridged into a high-current monoblock.

- 400 Watts into 8 Ohms
- 800 Watts into 4 Ohms
- >1000 Watts into 2 Ohms
- Ultra high current non-bridged design
- Fully discrete FET differential input stage
- Vertical MOSFET Voltage gain stage
- DC coupled to an ultra wideband bipolar output stage
- Very high linear damping with minimal feedback
- AC-coupled unbalanced input and true DC coupled balanced input
- Double-sided gold plated circuit boards
- 3.0kVA toroidal power transformer
- Low-impedance power supply filter capacitor array
- Graphite anodize aluminum and stainless steel finish
- Power supply and Bias status indicators
- 10 year warranty / 5 year transferrable
- Designed, manufactured and assembled in the USA

Rated Power:	400W/ch Class AB into 8Ω 800W/ch Class AB into 4Ω 1600W bridged Class AB into 8Ω
Frequency Response:	DC to 100kHz @ -3dB
Distortion:	<.02% from 10Hz to 20kHz at rated power
Gain:	26dB
Maximum Current:	>100 Amperes peak per channel
Noise:	-126dB
Input Impedance:	50kΩ unbalanced 10kΩ balanced
Output Impedance:	.03Ω from 20Hz to 20kHz .06Ω bridged from 20Hz to 20kHz
Power Supply:	3kVA toroidal power transformer. Dual independent rectification and 280,000uF of power supply filter capacitance
Dimension:	18" W x 19" D x 7.75" H
Weight :	110 lbs.